

## M-140i Multifunction calibrator



Multifunction calibrator M-140i is calibrator, determined mainly as standard of electric quantities in calibration laboratories. It can be used for calibration of electrical quantity meters from the field of voltage and current.

Calibrator is simpler and low cost version of model M-140.

### Basic parameters

Basic function of the calibrator is generating of the calibrated **DC/AC voltage** in the range from 0  $\mu\text{V}$  to 1000 V and **DC/AC current** in the range from 0 to 20 A . Using a 50-turn coil the current range can be extended from 50  $\mu\text{A}$  to 500 A. The best accuracy of the calibrator on DC voltage ranges is 0.0035%, on AC voltage ranges 0.03%, on DC current ranges 0.013% and on AC current ranges 0.055%. Maximum frequency range is from 20 Hz to 100 kHz for harmonic output waveform. For calibrations of the thermometers and temperature regulators, the function of **simulation of temperature sensors** is determined. Calibrator is able to simulate all TC sensors of the R, S, B, J, T, E, K and N types as well. TC cold junction compensation of is made by entering value from the keyboard.

### User comfort

M-140 Calibrator is equipped with a number of other functions which make its use easier. Among them belong possibility to set relative deviations from the actual value of the selected output signal, displaying of the output signal uncertainty, internal calibration procedure and others. Concept of the calibrator's control and indication uses a large area luminescence display on which all necessary information is concentrated. The control is performed by selection from the menu. Moreover, frequently used functions have firmly assigned keys with direct control. As standard calibrator is equipped with RS-232 serial port making it possible to be controlled by personal computer.

The calibrator can be included into MEATEST's WinQbase software calibration systems.

### Specification

#### DC/AC voltage

range	% of value + % of range	% of value + % of range	% of value + % of range	% of value + % of range
	<b>DC</b>	<b>20 Hz - 10 kHz</b>	<b>10 kHz - 50 kHz</b>	<b>50 kHz - 100 kHz</b>
0 mV - 20 mV **	0.05 + 0.0 + 10 $\mu\text{V}$	0.20 + 0.05 + 20 $\mu\text{V}$	0.20 + 0.10 + 20 $\mu\text{V}$	0.20 + 0.10 + 20 $\mu\text{V}$
20mV - 200mV	0.01 + 0.0 + 10 $\mu\text{V}$	0.1 + 0.03 + 20 $\mu\text{V}$	0.15 + 0.05 + 20 $\mu\text{V}$	0.15 + 0.05 + 20 $\mu\text{V}$
200 mV - 2 V	0.003 + 0.0008	0.025 + 0.005	0.05 + 0.01	0.05 + 0.01
2 V - 20 V	0.003 + 0.0005	0.025 + 0.005	0.05 + 0.03	0.05 + 0.03
20 V - 240 V	0.003 + 0.0005	0.025 + 0.010	--	--
240 V - 1000 V	0.005 + 0.005	0.03 + 0.02 *	--	--

\* valid for  $f < 1000$  Hz

\*\* DC voltage from 0  $\mu\text{V}$ , AC voltage from 1 mV

## DC/AC current

range	% of value + % of range	% of value + % of range	% of value + % of range	% of value + % of range
	DC	20 Hz - 1 kHz	1 kHz - 5 kHz	5 kHz - 10 kHz
1 $\mu$ A - 200 $\mu$ A	0.05 + 0.0 + 20 nA	0.15 + 0.0 + 20 nA	0.30 + 0.10 + 20 nA	--
200 $\mu$ A - 2 mA	0.02 + 0.005	0.07 + 0.01	0.20 + 0.05	0.20 + 0.05
2 mA - 20 mA	0.01 + 0.003	0.05 + 0.005	0.20 + 0.05	0.20 + 0.05
20 mA - 200 mA	0.01 + 0.003	0.05 + 0.005	0.20 + 0.05	0.20 + 0.05
200 mA - 2 A	0.015 + 0.005	0.05 + 0.005	--	--
2 A - 20 A	0.02 + 0.010	0.10 + 0.03	--	--

When option 130-50 Current coil is used, add uncertainty 0.3 % of the set current to the value specified in the above table. Output current is multiplied by factor 50.

## Thermocouple sensor simulation

<b>types</b>	R, S, B, J, T, E, K, N
<b>range of temperature</b>	-250 °C - 1820 °C
<b>temperature unc.</b>	0.4 °C - 4.0 °C
<b>temperature scale</b>	ITS 90, PTS 68

## Accessories (included)

Power line cable	1 pc
Operation manual	1 pc
Option 10/11 : Test cable for 1000V - 20 A, black/red	2 pcs

## Options (extra ordered)

Option 130-50	Current coil with 50 turns.  Suitable for clamp A-meters testing up to 500 A. Maximal recommended output current into the coil is 10 A.	
Option 10	Test cable 20A/1000V (black)	
Option 11	Test cable 20A/1000V (red)	
Option 20	Test cable BNC/BNC 1m	
Option 30	Test cable BNC/banana 1m	
Cable GPIB	IEEE488/IEEE488, 2m	
Cable RS-232	RS-232, 2m	
WinQbase	Application SW for making database of meters and for automatic meter calibration.	
<a href="#">CALIBER</a>	SW module for automatic calibration of multimeters.	